


Data Sheet | Item Number: 224-112

Conector pt iluminat, cu 2 conductori; buton cu reținere pe partea de iluminare; Par-
te iluminare: pt toate tipurile cond.; Parte inst.: pt conductori masivi; Seria 224; max.
2,5 mm²; Temperatură aer ambiant: max 60°C; 2,50 mm²; alb

<https://www.wago.com/224-112>



Color: alb



Dimensions in mm

Notes	
Safety information 1	in grounded power lines

Electrical data	
Ratings per IEC/EN	
Ratings per	EN 60664
Nominal voltage (II/2)	400 V
Rated surge voltage (II/2)	4 kV
Rated current	24 A
Legend (ratings)	(II / 2) ≙ Overvoltage category II / Pollution degree 2

Connection data

Connection points	3
Total number of potentials	1

Connection 1	
Connection type 1	Installation side
Connection technology	PUSH WIRE®
Actuation type	Push-in
Connectable conductor materials	Copper Aluminum
Connectable conductor materials (note)	Terminating Aluminum Conductors WAGO spring clamp terminal blocks are suitable for solid aluminum conductors up to 4 mm²/12 AWG if WAGO "Alu-Plus" Contact Paste 249-130 is used for termination. "Alu-Plus" Contact Paste Advantages: • Automatically destroys the oxide film during clamping. • Prevents fresh oxidation at the clamping point. • Prevents electrolytic corrosion between aluminum and copper conductors (in the same terminal block). • Provides long-term protection against corrosion. Using terminal blocks with CAGE CLAMP® Spring Pressure Connection Technology, aluminum conductors must first be cleaned with a blade and then immediately be inserted into the clamping units filled with "Alu-Plus" Contact Paste. For spring clamp connections with PUSH WIRE® connection technology, WAGO recommends that the aluminum conductor first be cleaned and then immediately inserted into the clamping unit filled with "Alu-Plus" contact paste. It is also possible to apply WAGO "Alu-Plus" additionally on the whole surface of the aluminum conductor before termination. Please note that the nominal currents must be adapted to the reduced conductivity of the aluminum conductors:: 2.5 mm² = 16 A 4 mm² = 22 A
Solid conductor	1 ... 2.5 mm² / 16 ... 14 AWG
Wiring direction	Side-entry wiring

Connection 2	
Connection type 2	Lighting side
Connection technology 2	CAGE CLAMP®
Number of connection points 2	1

Physical data	
Width	9,5 mm / 0.374 inci



Material Data	
Note (material data)	
Information on material specifications can be found here	
Color	alb
Fire load	0.047 MJ
Weight	2.1 g

Commercial data	
Product Group	7 (Push Wire Conn.)
eCl@ss 10.0	27-14-11-03
eCl@ss 9.0	27-14-11-03
ETIM 8.0	EC000447
ETIM 7.0	EC000447
PU (SPU)	1000 (100) Buc.
Packaging type	Box
Country of origin	CH
GTIN	4044918583596
Customs tariff number	85369010000

Approvals / Certificates		
General approvals		
Approval	Standard	Certificate Name
CSA DEKRA Certification B.V.	C22.2	1053495
UL UL International Germany GmbH	UL 486C	E69654
UL UL International Germany GmbH	EN 60998	CCA-2617-A1
UL UL International Germany GmbH	EN 60998	D-05895-A1 (EN60998-1 EN60998-2-2)
VDE VDE Prüf- und Zertifizierungsinstitut	EN 60998	40022792
Approvals for marine applications		
Approval	Standard	Certificate Name
ABS American Bureau of Ship-ping	-	18-HG1755093-PDA
BV Bureau Veritas S.A.	EN 60998	11914/D0 BV
DNV GL Det Norske Veritas, Ger-manischer Lloyd	EN 60998	TAE000015T
LR Lloyds Register	EN 60998	LR22207029TA

Downloads			
Documentation			
Bid Text			
224-112	19.02.2019	xml 3.46 KB	
224-112	21.02.2019	docx 15.55 KB	

CAD/CAE-Data



CAD data	
2D/3D Models 224-112	


CAE data	
EPLAN Data Portal 224-112	
WSCAD Universe 224-112	
ZUKEN Portal 224-112	

1 Compatible Products
1.1 Optional Accessories
1.1.1 Tool
1.1.1.1 "Alu-Plus" contact paste




Item No.: 249-130
Seringă; Conținut: 20 ml de pastă de contact „Alu-Plus”

Installation Notes
Conductor termination



Lighting Connectors (2.5 mm²), 224 Series




Strip conductor to 9 ... 11 mm (0.35 ... 0.43 inch).

Conductor termination





To connect: Press button fully, insert stripped conductor into square entry and release.



To remove: Press button and withdraw conductor.

Conductor termination



To connect: Insert stripped solid conductor into circular entry and push until it hits the backstop.

To remove: Hold conductor to be removed and twist alternately left and right while slightly pulling the connector.

Testing



Testing via separate test ports.